

ECMA/TC38-TG3/2015/026 (Rev. 1 – 15 April 2015)

Annex B2 - Product environmental attributes Notebooks and Tablets

The declaration may be published only when all rows and/or fields marked with * are filled-in (n.a. for not applicable). Additional information regarding each item may be found under P15.

Brand *	Lenovo	Logo	
Company name *	Lenovo		
Contact information *	Lenovo Global Environmental Affairs		$\Delta D \Delta V \Delta$
e-mail address	Alvin L Carter		Lenovo
	alcarter@lenovo.com		
Internet site *	http://www.lenovo.com/social_responsibility/us/en/environment	.html	
Additional information	The latest version of this document can be found at:		
	http://www.lenovo.com/ecodeclaration		

The company declares (The company declares (based on product specification or test results based obtained from sample testing), that the product						
conforms to the statemer	conforms to the statements given in this declaration.						
Type of product *	Notebook						
Commercial name *	ThinkBook 13s G3 ACN						
Model number *	20YA						
Issue date *	2021/2/2						
Intended market *	🛛 Global 📃 Europe 🗌 Asia, Pacific & Japan 🗌 Americas 🗌 Other						
Additional information							

This is an uncontrolled copy when in printed form. Please refer to the contact information for the latest version.

About Annex B2

Annex B2 reflects Product environmental attributes relevant for Computers and Computer Monitors. The following items from the ECMA-370 Main body are not shown in the template:

P4.1 – P4.3 Consumable materials

P9.1 TEC and Print speed

P10.2 - P10.3 Chemical emissions from printing products

P11.1 - P11.3 Consumable materials for printing products.

Model nu	umber *	20YA Logo			
Issue date * 2021/2/		2021/2/2	.eno\	/O	
	t environ	mental attributes - Legal requirements	Require		met
Item			Yes	No	n.a.
P1		ous substances and preparations			
P1.1*		s do comply with current European RoHS Directive. (See legal reference and NOTE B1)			
P1.2*	Comme	s do not contain Asbestos (see legal reference). nt: Legal reference has no maximum concentration value.	\square		
P1.3*	hydrobro trichloro	s do not contain Ozone Depleting Substances: Chlorofluorocarbons (CFC), pmofluorocarbons (HBFC), hydrochlorofluorcarbons (HCFC), Halons, carbontetrachloride, 1,1,1- ethane, methyl bromide (see legal reference). Comment: Legal reference has no maximum ration values.			
P1.4*	terpheny	s do not contain more than; 0,005% polychlorinated biphenyl (PCB), 0,005% polychlorinated /I (PCT) in preparations (see legal reference).			
P1.5*	chain co	s do not contain more than 0,1% short chain chloroparaffins (SCCP) with 10-13 carbon atoms in the Intaining at least 48% per mass of chlorine in the SCCP (see legal reference).			
P1.6*	(see leg	th direct and prolonged skin contact do not release nickel in concentrations above 0,5 μg/cm²/weeł al reference). nt: Max limit in legal reference when tested according to EN1811:2011-5.	(🔀		
P1.7*	REACH https://	Article 33 information about substances in articles is available at (add URL or mail contact): www.lenovo.com/us/en/Lenovo-REACH-SVHC-Disclosure	\boxtimes		
P2	Batterie				
P2.1*	symbol.	oduct contains a battery or an accumulator, the battery/accumulator is labeled with the disposal Information on proper disposal is provided in user manual. (See legal reference)	\square		
P2.2*	Batteries referenc	s or accumulators do not contain more than 0,0005% of mercury or 0,002% of cadmium. (See lega æ)	I 🛛		
P2.3*	Batteries	s and accumulators are readily removable. (See legal reference)	\boxtimes		
P3	Conform	nity verification & Eco design (ErP)			
P3.1*	The Dec	duct is CE-marked to show conformance with applicable legal requirements (see legal reference). claration of Conformity can be requested at (add link or e-mail address): ww.lenovo.com/social_responsibility/us/en/ec_doc			
P3.2*	The proc	duct complies with the Eco design requirements for energy-related products, al reference).	\boxtimes		
	Require	d information is; i given in item P15 or added to this document, available at (add URL): www.lenovo.com/us/en/compliance/eco-declaration			
P5		t packaging			
P5.1*	Packagi	ng and packaging components do not contain more than 0,01% lead, mercury, cadmium an ent chromium by weight of these together.	nd 🔀		
P5.2*	The pac	kaging materials are marked with abbreviations and numbers indicating the nature of the material(se legal reference).	s) 🔀		
			ol 🔀		
P5.3*	(see leg	duct packaging material is free from ozone depleting substances as specified in the Montreal Protoco al reference). nt: Legal reference has no maximum concentration values.			
P5.3*	(see leg Comme				

NOTE B1 Restriction applies to the homogeneous material, unless other specified and expressed in weight %. Stating "Yes" means that the product is compliant with the mandatory requirements.

Model nu	umber *	20YA	Logo	Long		
Issue dat	te *	2021/2/2		Lend	JVO	Эн
Product	environ	mental attributes - Market requirements (See General NOTE GN	below)			
		onmental conscious design		Require		met
Item P7		tory to fill in. Additional information regarding each item may be found under P14. Disassembly, recycling		Yes	No	n.a.
P7.1*	<u> </u>	at have to be treated separately are easily separable				
P7.2*		naterials in covers/housing have no surface coating.				⊢⊢
P7.3*		arts > 100 g consist of one material or of easily separable materials.		<u> </u>		
P7.4*		arts > 25 g have material codes according to ISO 11469 referring ISO 1043-4.			H	
P7.5	-	arts are free from metal inlays or have inlays that can be removed with commonly a	available tools			
P7.6*	-	re easily separable. (This requirement does not apply to safety/regulatory labels).		··		⊢⊢
	Product					
P7.7*		ng can be done e.g. with processor, memory, cards or drives				
P7.8*		ng can be done using commonly available tools			Ħ	Ħ
P7.9	Spare pa	arts are available after end of production for: 5 years				Ē
P7.10		s available after end of production for: 5 years				Ħ
		and substance requirements				
P7.11*	Product of Material	cover/housing material type (e.g. plastics, metal, aluminum):) type: <i>Al</i> Material type: <i>PC+ABS</i> Materia	al type: <i>Alum</i>	inum		
P7.12	Insulatio	n materials of external electrical cables are PVC free.		\boxtimes		
P7.13	Insulatio	n materials of internal electrical cables are PVC free.		\boxtimes		
P7.14	weight (* polyvinyl	plastic casing/cover parts > 25 g contain no more than 0,1% weight (1000 ppm) b 1000 ppm) chlorine attributable to brominated flame retardants, chlorinated flame chloride or 0,3% weight (3000 ppm) bromine and 0,3% weight (3000 ppm) chlorine i in 25% post-consumer recycled content.	e retardants,	and		
P7.15		arcuit boards, PCBs (without components) are low halogen: all □ PCBs > 25 g ⊠ ed in IEC 61249-2-21. (See 1NOTE B2)	are low halo	gen	\square	
P7.16	Flame re Marking:	tarded plastic parts > 25 g in covers / housings are marked according ISO 1043-4:				\square
P7.17		nemical specifications of flame retardants in printed circuit boards > 25 g (without c PA (additive), TBBPA (reactive) (See NOTE B3), Other: DOPD , CAS #: 359				
	according	nemical specifications of flame retardants in printed circuit boards (without compon g ISO 1043-4: <i>NA</i>				\boxtimes
P7.18	concentr 1. Chem 2. Chem	ame retarded plastic parts > 25 g contain the following flame retardant substance ations above 0,1%: ical name: , CAS #: (See NOTE B4) ical name: , CAS #:	es/preparation	is in		
	<u>Alt. 2: </u> Ch	ical name: , CAS #: " nemical specifications of flame retardants in plastic parts > 25 g according ISO 104				
P7.19	assigned	; parts > 25 g, flame retardant substances/preparations above 0,1% are used which I the following Risk phrases; and Hazard statements:	n have been			
D7 00t			See note B5)			
P7.20*	Postcons	sumer recycled plastic material content is used in the product (See Note B6):		\boxtimes		
	a) Oft ape or	It least one of the two alternatives below shall be answered; otal plastic parts' weight > 25 g, the postconsumer recycled plastic material conter ercentage of total plastic by weight) is 2.1% . e weight of recycled material is 2.6 g	it (calculated a	as		

GENERAL NOTE Standard references should direct to the latest version of a standard. If an older version of a standard is used, section P15 shall be used for explanation.

NOTE B2 IEC 61249-2-21 defines maximum limits of 900 ppm for each of the substances chlorine and bromine and a maximum limit of 1500ppm of these substances combined. The standard does not address fluorine, iodine and astatine which are included in the group of halogens.

NOTE B3 and B4 A Guidance document on Chemical substances is available; see http://www.ecma-international.org/publications/standards/Ecma-370.htm

NOTE B5 If a certain substance has been assigned a certain risk phrases / hazard statement in the referenced source, this does not necessarily mean the substance has been tested for all of the hazards referred to by a certain customer.

NOTE B6 Applies to a product containing plastic parts whose combined weight exceeds 100 g with the exception of printed circuit boards, cables, connectors and electronic components and bio-based plastic material.

Model number *	20YA	Logo	
Issue date *	2021/2/2		Lenovo
Product environment	nental attributes - Market requirements (continued)		Requirement met

Item

Requirement metYesNon.a.

	Material and sub	stance requirements	(continued)			
P7.21*		material content is use		IOTE B7):		
	If VES: at least or	ne of the two alternative	as below shall be answ	vered:		
					ated as a percentage of	
		by weight) is 0%.				
	or	, , ,				
		of the biobased plastic				
P7.22*		free from mercury, i.e.				
B A		specify: Number of la	mps: and maxin	num mercury content p	per lamp: mg	
P8	Batteries			Dissists		
P8.1*	,	composition: Lithium I	on/Litnium Mangane	se Dioxide		
P9		otion (See NOTE B8)				
P9.1		e following power leve	ls or energy consumpt			
Energy mo	de ^	Power level at	Power level at 115 V AC	Power level at	Reference/Standard for energy modes and test method *	
Peak (On-	max	100 V AC	65 W	230 V AC	Full load	
reak (OII-	illax)	00 00	05 11	00 00	T un load	
Categor	y 2					
	State - WOL	5.208 W	5.424 W	5.796 W	Use for ENERGY STAR V6	
Enabled					registration (P _{idle})	
Long Idle	State - WOL	2.472 W	2.544 W	2.616 W	Use for ENERGY STAR V6	
Enabled					registration (P _{idle})	
	- WOL Enabled /	0.564 W	0.576 W	0.636 W	Use for ENERGY STAR V6	
Disabled					registration(P _{sleep})	
Off (S5) -	WOL Enabled /	0.324 W	0.348 W	0.360 W	Use for ENERGY STAR V6	
Disabled					registration, ErP(P _{off})	
	a d	0.13 W	0.13 W	0.13 W		
EPS No-lo			0.13 VV	0.73 VV		
	supply / charger plugged in the sconnected from the product.)					
PTEC *(2)		W	W	W		
Typical En	ergy Consumption					
Etec *(2)		18.29Wh/year	19.01kWh/year	20.26kWh/year	E _{TEC} = (8760/1000) x (P _{off} x 0.25 +	
Annual En	ergy Consumption				$P_{sleep} \times 0.35 + P_{long_ldle} \times 0.10 +$	
					P _{short_Idle} x 0.30)	
					led; Pidle: Idle State - WOL Enabled	
External P	ower Supply Efficie	ncy Level (Internationa	I Efficiency Marking Pi	rotocol) * : VI		
Display res	solution * : 2.304 m	egapixels				
Default tim	e to enter energy s	ave mode: 30 minutes				
P9.2*	Information about	the energy save funct	ion is provided with the	e product.		
P9.3		class (monitors only):		- F		
P10						
P10	Emissions	- Declared according t		E BO)		
P10.1		Mode description	0100 9290 (See NOT	E B9) Statistical upper limit A-weighted sound power level, L _{WA,c} (B		
1 10.1	Idle	* Idle mode		* 2.7		
		* Operating (CPU)		* 4.2		
	Operation					
		Declared A-weighted sour			on desktop – idle)	
	Other mode	Declared A-weighted sour	ad pressure level (dB) L_{pAr}	n 35 (operator positi	on desktop – operating)	
		ing to: 🔀 ISO 7779	1	1		
		Other	(only if not covered b			

NOTE B7 The following is to be excluded from the calculation of percentage: printed circuit boards, labels, cables, connectors and electronic components and postconsumer recycled plastic

NOTE B8 A Guidance document on Energy Efficiency is available; see <u>http://www.ecma-international.org/publications/standards/Ecma-370.htm</u>

NOTE B9 A Guidance document on Acoustic Noise is available; see http://www.ecma-international.org/publications/standards/Ecma-370.htm

Model nu	Imber *	20YA			Logo			
Issue dat	te *	2021/2/2				Lenc		
Product	environ	nental attribu	tes - Market requirement	ts (continued)		Require	ment	met
Item						Yes	No	n.a.
		magnetic emiss						
P10.4	program	ı(s): MPŔ-II(3 pi l	the requirement for low frequence of the requirement of the second secon	uency electromagnetic field	s of the following volur	ntary 🔀		
P12		mics for compu						
P12.1*			gonomic requirements of ISC					
P12.2*	The phy	sical input devic	e meets the requirements of	SO 9995 and ISO 9241-41	0.	\square		
P13		ing and docum						
P13.1*	Product Product	packaging mate						
P13.2*			ackaging is free from PVC.			\boxtimes		
P13.3*	consum	er recovered fibe	rugated fiberboard packagir r content: 100 %		percentage of minimu			
P13.4*		media for user a ronic, ⊠Paper,	nd product documentation (tie	ck box):				
P13.5	Ùser an		is item if paper documentatic entation on paper media is c			\boxtimes		
	Element	chlorine-free al chlorine-free ed chlorine-free						
P14	Volunta	ry programs						
P14.1			equirements of the following	voluntary program(s):				
P15	Eco-lab Eco-lab	el:	Criteria version: V8.0 Criteria version: Criteria version: (See NOTE B10)	Date: 2021/1/14 Date: Date:	Product category: 2 Product category: Product category:			
P9			(See NOTE BTO) f specific configuration ma	v vary: description of the	tostad product confi	auration:		
13	NOTE: S informat knowled provided	Supplier makes r ion contained in Ige available at t I here is approxi	to representations, guarantee this document. All information the time of completion, and sumate and provided for informa-	es, assurances or warrantie n provided by supplier in th ipplier shall have no obligat	s whether express or i is document is provide ion to update such info	mplied, regardir d based on sup ormation. The in	olier's formatio	on
P9		ergy Star Qualifie	d Notebooks & Tablet Comp v/index.cfm?fuseaction=find					

NOTE B10 Additional lines may be inserted to declare further items, by positioning the cursor at the far right of the row and hitting the <Enter> key.

Legal references Europe Annex B2

Reference	Declaration item
Directive 2011/65/EU (RoHS Directive) * * Specific exemptions apply for certain products and applications.	P1.1
Regulation (EC) 1907/2006(REACH, Annex XVII	P1.2, P1.4, P1.6, P1.7
Regulation (EC) 2037/2000, 2038/2000, 2039/2000 (Marketing and use of Ozone layer depleting substances)	P1.3, P5.3
Norwegian regulation relating to restrictions on the use of certain dangerous chemicals 20.12.2002	P1.5
Directive 2013/56/EC (Battery and accumulators Directive) * * These provisions shall not apply where, for safety, performance, medical or data integrity reasons, continuity of power supply is necessary and requires a permanent connection between the appliance and the battery or accumulator.	P2.1, P2.2, P2,3, P8.1
Directive 2006/95/EC (Low Voltage Directive)	P3.1
Directive 2004/108/EC (EMC Directive)	P3.1
Directive 1999/5/EC (R&TTE Directive)	P3.1
Regulation (EC) 801/2013 amending Regulation (EC) No 1275/2008 with regard to ecodesign requirements for standby, off mode electric power consumption of electrical and electronic household and office equipment, and amending Regulation (EC) No 642/2009 with regard to ecodesign requirements for televisions	P3.1, P3.2
Regulation (EC) No 1272/2008 (CLP Regulation)	P7.19
Directive 2004/12/EC (Packaging Directive)	P5.1
Decision 97/129/EC (Secondary packaging legislation)	P5.2
Directive 2012/19/EU (WEEE directive)	P6.1

Lenovo ErP Lot3 Information Sheet - PC / Notebook -

As required by COMMISSION REGULATION (EU) No 617/2013 of 26 June 2013 implementing Directive 2009/125/EC of the European Parliament and of the Council with regard to ecodesign requirements for computers and computer servers (ErP Lot3).

Products scope of this sheet:

Desktop computer, integrated desktop computer, and notebook computer

This document is only valid in connection with the IT Eco Declaration of the specific Product.

Commercial name	ThinkBook 13s G3 ACN	Logo		
Model Number	20YA		Lonovo	
Issue Date	2021/2/2		Lenovo	
Additional information				

(d)	year of manufacture:				2020	
e)	Etec value (kWh) per ErP Lot 3 Catego disabled and if the system is tested with				cards (dGfx) are	
f)	Etec value (kWh) per ErP Lot 3 Categor enable	ry and capability adjust	ments applied when a	all discrete graphics of	cards (dGfx) are	
		Category A (according to ErP Lot 3)	Category B (according to ErP Lot 3)	Category C (according to ErP Lot 3)	Category D (according to ErP Lot 3)	
	Memory over base [GB]	16				
ents ting	Additional internal storage	No (Yes / No)	(Yes / No)	(Yes / No)	(Yes / No)	
capability adjustments applied during testing	Discrete television tuner	No (Yes / No)	(Yes / No)	(Yes / No)	(Yes / No)	
ability a lied du	Discrete Audio Card	No (Yes / No)	(Yes / No)	(Yes / No)	(Yes / No)	
cape appl	Discrete graphics Card(s) [number / #]	No #: (Yes / No)	#: (Yes / No)	#: (Yes / No)	#: (Yes / No)	
	Category of discrete graphics Card(s)					
esults	Etec Value (kWh) - dGfx disabled all discrete graphics cards (dGfx) are disabled/ UMA is active for switchable graphics/ product has no graphics cards (dGfx)	10.06				
Test results	Etec Value (kWh) - dGfx enabled all discrete graphics cards (dGfx) are enabled					
(g)	Idle state power demand (Watts);			μ.	2.87	
h)	Sleep mode power demand (Watts);				0.69	
i)	Sleep mode with WOL enabled power de	emand (Watts) (where	enabled);		0.69	
j)	Off mode power demand (Watts);				0.37	
(k)	Off mode with WOL enabled power dem	and (Watts) (where en	abled);		0.37	
[])	Internal power supply efficiency at 10 %, 20 %, 50 % and 100 % of rated output power (if applicable):					
	10% 20% 50%	100% Avera	ige			
(m)	external power supply efficiency (if appli	cable)*:				
	Average active efficiency: 89.5% meet Le	evel VI				
	*internal note: show values for all available external p					
(0)	Minimum number of loading cycles that	the batteries can withs	and (applies only to r	notebook computers):	300 cycles	
(p-1)	Measurement methodology used to dete	ermine information mer	itioned in points (I) – i	nternal PSU efficiency	: NA	
(p-2)	Measurement methodology used to dete ENERGY STAR® Program Requirement		e External Ac-Dc an			

power as defined in Point P9.1 in the Product IT Eco Declaration: IEC 62623 (q) Sequence of steps for achieving a stable condition with respect to power demand:: Power on -> Wait 5 minutes ->Stable condition (r) Description of how sleep and/or off mode was selected or programmed: Begin menu -> Power -> Select sleep or off mode (s) Sequence of events required to reach the mode where the equipment automatically changes to sleep and/or off mode: NA (t) Duration of idle state condition before the computer automatically reaches sleep mode, or another condition which does not exceed the applicable power demand requirements for sleep mode (in minutes): 30 mins (u) Length of time after a period of user inactivity in which the computer automatically reaches a power N/A N/A								
a defined in Point P9.1 in the Product IT Eco Declaration: IEC 62623 (q) Sequence of steps for achieving a stable condition with respect to power demand:: Power on -> Wait 5 minutes ->Stable condition (r) Description of how sleep and/or off mode was selected or programmed: Begin menu -> Power -> Select sleep or off mode (s) Sequence of events required to reach the mode where the equipment automatically changes to sleep and/or off mode://A 30 mins (t) Duration of idle state condition before the computer automatically reaches sleep mode, or another condition which does not exceed the applicable power demand requirements for sleep mode, or another mode that has a lower power demand requirement than sleep mode (in minutes): 10 mins (u) Length of time affer a period of user inactivity in which the computer automatically reaches a power mode that has a lower power demand requirement than sleep mode (in minutes): 10 mins (v) Length of time before the display sleep mode is set to activate after user inactivity (in minutes): 10 mins (w) user information on how to enable the power management functionality: Refer to User Guide (z) test parameters for measurements:: — test voltage in V and frequency in Hz, — total harmonic distortion of the electricity supply system, — information and documentation on the instrumentation, set-up and circuits used for electrical testing: 230V50HZ-22%-Edifion 2.0, 2011-01, Section 4, IEC62301 Add	(p-3)	Measurement metho		points (o) – loading cycles batteries:				
(q) Sequence of steps for achieving a stable condition with respect to power demand:: Power on -> Wait 5 minutes ->Stable condition (r) Description of how sleep and/or off mode was selected or programmed: Begin menu -> Power -> Select sleep or off mode (s) Sequence of events required to reach the mode where the equipment automatically changes to sleep and/or off mode: NA (t) Duration of idle state condition before the computer automatically reaches sleep mode, or another condition which does not exceed the applicable power demand requirements for sleep mode (or minutes): 30 mins (u) Length of time after a period of user inactivity in which the computer automatically reaches a power N/A N/A (v) Length of time after a period of user inactivity in which the computer automatically reaches a power M/A N/A (w) Length of time after a period of user inactivity in which the computer automatically reaches a power M/A N/A (w) Length of time before the display sleep mode is set to activate after user inactivity (in minutes): 10 mins (w) Length of time before the display sleep mode is set to activate after user inactivity (in minutes): 10 mins (w) Information on how to enable the power management functionality: Refer to User Guide (2) test parameters for measurements: test voltage in V and frequency in	(p-4)			maximum, idle, sleep, off mode				
Power on -> Wait 5 minutes ->Stable condition (1) Description of how sleep and/or off mode was selected or programmed: Begin menu -> Power -> Select sleep or off mode (5) Sequence of events required to reach the mode where the equipment automatically changes to sleep and/or off mode:NA (1) Duration of idle state condition before the computer automatically reaches sleep mode (in minutes): 30 mins (1) Length of time after a period of user inactivity in which the computer automatically reaches a power mode that has a lower power demand requirement than sleep mode (in minutes): N/A (1) Length of time after a period of user inactivity in which the computer automatically reaches a power minutes): N/A (2) Length of time before the display sleep mode is set to activate after user inactivity (in minutes): 10 mins (N) Longth of time before the display sleep mode is set to activate after user inactivity (in minutes): 10 mins (W) Length of time before the display sleep mode is set to activate after user inactivity (in minutes): 10 mins (W) Length of time before the display sleep mode is set to activate after user inactivity (in minutes): 10 mins (W) Length of time before the display sleep mode is set to activate after user inactivity (in minutes): 10 mins (W) Length			IEC 62623					
(r) Description of how sleep and/or off mode was selected or programmed: Begin menu -> Power -> Select sleep or off mode (s) Sequence of events required to reach the mode where the equipment automatically changes to sleep and/or off mode:NA (t) Duration of idle state condition before the computer automatically reaches sleep mode. (or another condition which does not exceed the applicable power demand requirements for sleep mode. (in minutes): 30 mins (u) Length of time after a period of user inactivity in which the computer automatically reaches a power mode that has a lower power demand requirement than sleep mode (in minutes): 10 mins (u) Length of time before the display sleep mode is set to activate after user inactivity (in minutes): 10 mins (w) Information on the energy-saving potential of power management functionality: N/A (x) user information on how to enable the power management functionality: Refer to User Guide (z) test parameters for measurements: test or club at the site of the adverted at the structure and a documentation on the instrumentation, set-up and circuits used for electrical testing: 230/50HZ-23%-Edition 2.0, 2011-01, Section 4, IEC62301 Additional Notebook Battery Information: Intermal/built-in Battery Intermal/built-in Battery Intermal/built-in Battery Bios Backup Battery Intermal/built-in Battery Intermal/built-in Battery <td>(q)</td> <td>Sequence of steps for</td> <td>or achieving a stable condition with respect to power</td> <td>demand::</td> <td></td>	(q)	Sequence of steps for	or achieving a stable condition with respect to power	demand::				
Begin menu -> Power -> Select sleep or off mode (s) Sequence of events required to reach the mode where the equipment automatically changes to sleep and/or off mode:/M4 (t) Duration of idle state condition before the computer automatically reaches sleep mode, or another condition which does not exceed the applicable power demand requirements for sleep mode, (in minutes): 30 mins (u) Length of time after a period of user inactivity in which the computer automatically reaches a power N/A N/A (u) Length of time before the display sleep mode is set to activate after user inactivity (in minutes): 10 mins (v) Length of time before the display sleep mode is set to activate after user inactivity (in minutes): 10 mins (w) Information on the energy-saving potential of power management functionality: Refer to User Guide (x) user information on how to enable the power management functionality: Refer to User Guide (z) test parameters for measurements: — test voltage in V and frequency in Hz, — total harmonic distortion of the electricity supply system, — information and documentation on the instrumentation, set-up and circuits used for electrical testing: 230V50HZ-2%-Edition 2.0, 2011-01, Section 4, IEC62301 Additional Notebook Battery [Information: The battery[ies] in this product cannot be easily Battery[ies] user replaceable n/a The battery[ies] in t			Power on -> Wait 5 minutes ->Stable con	ndition				
(s) Sequence of events required to reach the mode where the equipment automatically changes to sleep and/or off mode: NA (t) Duration of idle state condition before the computer automatically reaches sleep mode, or another condition which does not exceed the applicable power demand requirements for sleep mode (in minutes): 30 mins (u) Length of time after a period of user inactivity in which the computer automatically reaches a power mode that has a lower power demand requirements for sleep mode (in minutes): 10 mins (v) Length of time before the display sleep mode is set to activate after user inactivity (in minutes): 10 mins (w) Information on the energy-saving potential of power management functionality: N/A (x) user information on how to enable the power management functionality: Refer to User Guide (x) user information on how to enable the power management functionality: Refer to User Guide (z) test parameters for measurements: — test voltage in V and frequency in Hz, — total harmonic distortion of the electricity supply system, — information and documentation on the instrumentation, set-up and circuits used for electrical testing: 230V50HZ-2%-Edition 2.0, 2011-01, Section 4, IEC62301 Additional Notebook Battery Information: Battery[ies] not user replaceable n/a The battery[ies] in this product cannot be easily replaced by users themselves. ¹ Imernal/built-in Battery Imerelaced by users themsel	(r)	Description of how s	leep and/or off mode was selected or programmed:					
off mode:NA (t) Duration of idle state condition before the computer automatically reaches sleep mode, or another condition which does not exceed the applicable power demand requirements for sleep mode (in minutes): 30 mins (u) Length of time after a period of user inactivity in which the computer automatically reaches a power mode that has a lower power demand requirement than sleep mode (in minutes): N/A (v) Length of time before the display sleep mode is set to activate after user inactivity (in minutes): 10 mins (w) Information on the energy-saving potential of power management functionality: N/A (x) user information on how to enable the power management functionality: Refer to User Guide (z) test parameters for measurements: — test voltage in V and frequency in Hz, — total harmonic distortion of the electricity supply system, — information and documentation on the instrumentation, set-up and circuits used for electrical testing: 230V50HZ-2%-Edition 2.0, 2011-01, Section 4, IEC62301 Additional Notebook Battery Information: Battery[ies] not user replaceable n/a The battery[ies] in this product cannot be easily replaced by users themselves. ") Internal/built-in Battery Image: Image			Begin menu -> Power -> Select sleep or c	off mode				
condition which does not exceed the applicable power demand requirements for sleep mode (in minutes): Joinths (u) Length of time after a period of user inactivity in which the computer automatically reaches a power N/A (u) Length of time after a period of user inactivity in which the computer automatically reaches a power N/A (u) Length of time before the display sleep mode is set to activate after user inactivity (in minutes): 10 mins (v) Length of time before the display sleep mode is set to activate after user inactivity (in minutes): 10 mins (w) Information on the energy-saving potential of power management functionality: Refer to User Guide (x) user information on how to enable the power management functionality: Refer to User Guide (z) test parameters for measurements: — test voltage in V and frequency in Hz, — total harmonic distortion of the electricity supply system, — information and documentation on the instrumentation, set-up and circuits used for electrical testing: 230V50HZ-2%-Edition 2.0, 2011-01, Section 4, IEC62301 Additional Notebook Battery Information: Battery[ies] not user replaceable Battery[ies] user replaceable n/a The battery[ies] in this product cannot be easily replaced by users themselves. 1) Internal/built-in Battery Image: Ima	(s)							
mode that has a lower power demand requirement than sleep mode (in minutes): Image: Content of time before the display sleep mode is set to activate after user inactivity (in minutes): 10 mins (w) Information on the energy-saving potential of power management functionality: Refer to User Guide 10 mins (x) user information on how to enable the power management functionality: Refer to User Guide 10 mins (x) user information on how to enable the power management functionality: Refer to User Guide 10 mins (z) test parameters for measurements: — test voltage in V and frequency in Hz, — total harmonic distortion of the electricity supply system, — information and documentation on the instrumentation, set-up and circuits used for electrical testing: 230V50HZ-2%-Edition 2.0, 2011-01, Section 4, IEC62301 Additional Notebook Battery Information:	(t)	condition which does	s not exceed the applicable power demand requirement	ents for sleep mode (in minutes):	30 mins			
(w) Information on the energy-saving potential of power management functionality: <i>Refer to User Guide</i> (x) user information on how to enable the power management functionality: <i>Refer to User Guide</i> (z) test parameters for measurements: — test voltage in V and frequency in Hz, — total harmonic distortion of the electricity supply system, — information and documentation on the instrumentation, set-up and circuits used for electrical testing: 230V50HZ-2%-Edition 2.0, 2011-01, Section 4, IEC62301 Additional Notebook Battery Information: Battery[ies] not user replaceable Battery[ies] user replaceable The battery[ies] in this product cannot be easily replaced by users themselves. ¹) Internal/built-in Battery Internal/built-in Battery Internal/built-in Battery Internal Bios Backup Battery Internal Internal Internal Other: Internal Internal Internal Internal	(u)	mode that has a low	wer power demand requirement than sleep mode (in	n minutes):	N/A			
Refer to User Guide (x) user information on how to enable the power management functionality: Refer to User Guide (z) test parameters for measurements: — test voltage in V and frequency in Hz, — total harmonic distortion of the electricity supply system, — information and documentation on the instrumentation, set-up and circuits used for electrical testing: 230V50HZ-2%-Edition 2.0, 2011-01, Section 4, IEC62301 Additional Notebook Battery Information: Internal/beilt-in Battery[ies] not user replaceable Battery[ies] user replaceable n/a The battery[ies] in this product cannot be easily replaceable Internal/built-in Battery Internal/built-in Batt	(V)							
(x) user information on how to enable the power management functionality: Refer to User Guide (z) test parameters for measurements: — test voltage in V and frequency in Hz, — total harmonic distortion of the electricity supply system, — information and documentation on the instrumentation, set-up and circuits used for electrical testing: 230V50HZ-2%-Edition 2.0, 2011-01, Section 4, IEC62301 Additional Notebook Battery Information: Battery[ies] not user replaceable Battery[ies] user replaceable n/a Internal/built-in Battery Image: Start St	(\vv)			nanty.				
Refer to User Guide (2) test parameters for measurements: — test voltage in V and frequency in Hz, — total harmonic distortion of the electricity supply system, — information and documentation on the instrumentation, set-up and circuits used for electrical testing: 230V50HZ-2%-Edition 2.0, 2011-01, Section 4, IEC62301 Additional Notebook Battery Information: Mattery[ies] not user replaceable Battery[ies] not user replaceable Battery[ies] user replaceable n/a The battery[ies] in this product cannot be easily replaced by users themselves. ¹) Internal/built-in Battery Image: Colspan="2">Image: Colspan="2">Image: Colspan="2">Colspan="2"Colspan="2"Colspan="2"Colspan=""2"Colspan="2"Colsp	()	upor information and						
(z) test parameters for measurements: — test voltage in V and frequency in Hz, — total harmonic distortion of the electricity supply system, — information and documentation on the instrumentation, set-up and circuits used for electrical testing: 230V50HZ-2%-Edition 2.0, 2011-01, Section 4, IEC62301 Additional Notebook Battery Information: Battery[ies] not user replaceable Battery[ies] user replaceable n/a The battery[ies] in this product cannot be easily replaced by users themselves. 1) Internal/built-in Battery Internal/built-in	(x)	user information on r						
electricity supply system, — information and documentation on the instrumentation, set-up and circuits used 5000000000000000000000000000000000000	(-)							
Additional Notebook Battery Information: Battery[ies] not user replaceable The battery[ies] in this product cannot be easily replaced by users themselves. ¹⁾ Battery[ies] user replaceable n/a Internal/built-in Battery Image: Comparison of the second	(2)	electricity supply sys						
Battery[ies] notuser replaceableBattery[ies] user replaceablen/aThe battery[ies] in this product cannot be easily replaced by users themselves. 1)Image: Image:				4, IEC62301				
The battery[ies] in this product cannot be easily replaced by users themselves. 1) Internal/built-in Battery Internal/built-in Battery Image: Comparison of the product cannot be easily replaced by users themselves. 1) External/detachable Battery Image: Comparison of the product cannot be easily replaced by users themselves. 1) Bios Backup Battery Image: Comparison of the product cannot be easily replaced by users themselves. 1) Other: Image: Comparison of the product cannot be easily replaced by users themselves. 1)	Additio	nal Notebook Batter		Battery/ies] user replaceable	n/a			
External/detachable Battery Image: Constraint of the sector of the sec			The battery[ies] in this product cannot be easily		Ti/a			
Bios Backup Battery Image: Comparison of the sector of t	Internal/	/built-in Battery						
Other: Image: Control of the second	Externa	I/detachable Battery						
	Bios Ba	ckup Battery						
Additional information	Other:							
	Addition	al information						
	s baterías o	de este producto no pueden s	er sustituidas fácilmente por los propios usuarios.	и.				
умулаторната[ите] батерия[и] в този продукт не може да се замени[ят] лесно от самите потребители. s baterías de este producto no pueden ser sustituídas fácilmente por los propios usuarios. mônu bateric/bateríu / tomto vironkul pv peměli provádřt sami uživatelé	ugeren kan	ikke uden videre udskifte bat	teriet/batterierne i dette produkt.	verden				
s baterías de este producto no pueden ser sustituidas fácilmente por los propios usuarios. měnu baterie/baterií v tomto výrobku by neměli provádět sami uživatelé. ugeren kan ikke uden videre udskifte batteriet/batterierne i dette produkt.	asutajad ei s	saa selle toote akut/akusid ise	e hõlpsasti asendada.					
s baterías de este producto no pueden ser sustituidas fácilmente por los propios usuarios. mēnu baterie/baterií v tomto výrobku by neměli provádět sami uživatelé. ugeren kan ikke uden videre udskifte batteriet/batterierne i dette produkt. re Akku/die Akkus dieses Produkts kann/können nicht ohne weiteres vom Benutzer selbst ausgetauscht werden. usutajad ei saa selle toote akut/akusid ise hõlpsasti asendada.	/les batterie	e(s présente(s) dans ce produ	uit ne peuvent être facilement remplacée(s) par les utilisateurs eu	ıx-mêmes.				
s baterías de este producto no pueden ser sustituidas fácilmente por los propios usuarios. ménu baterie/bateríl v tomto výrobku by neměli provádět sami uživatelé. ugeren kan likke uden videre udskitife batterierich dette produkt. er Akku/die Akkus dieses Produkts kann/können nicht ohne weiteres vom Benutzer selbst ausgetauscht werden. sutajad ei saa selle toote akut/akusid ise hölpsasti asendada. µπαταρία[-ες] στο προϊόν αυτό δεν μπορούν να αντικατασταθούν εύκολα από τους ίδιους τους χρήστες //les batterie(s présente(s) dans ce produit ne peuvent être facilement remplacée(s) par les utilisateurs eux-mêmes.	a batteria/le	batterie in questo prodotto no	on può/possono essere facilmente sostituita/e dall'utente.					
s baterías de este producto no pueden ser sustituidas fácilmente por los propios usuarios. imênu baterie/baterií v tomto výrobku by neměli provádět sami uživatelé. ugeren kan ikke uden videre udskifte batteriet/batterierne i dette produkt. er Akku/die Akkus dieses Produkts kann/können nicht ohne weiteres vom Benutzer selbst ausgetauscht werden. isutajad ei saa selle toote akut/akusid ise hõlpsasti asendada. µπαταρία[-sc] στο προϊόν αυτό δεν µπορούν να αντικατασταθούν εύκολα από τους ίδιους τους χρήστες //les batterie(s présente(s) dans ce produit ne peuvent être facilement remplacée(s) par les utilisateurs eux-mêmes. risnik ne može lako zamijeniti Bateriju sam u ovom proizvodu.	o gaminio b	aterijos [baterijų] pats vartoto	jas negali lengvai pakeisti.					
s baterías de este producto no pueden ser sustituidas fácilmente por los propios usuarios. iménu baterie/bateríi v tomto výrobku by neměli provádět sami uživatelé. ugeren kan like uden videre udskifite batteriet/batterierne i dette produkt. er Akku/die Akkus dieses Produkts kann/können nicht ohne weiteres vom Benutzer selbst ausgetauscht werden. sutajad ei saa selle toote akut/akusid ise hölpsasti asendada. µπαταρία[-ɛɛ] στο προϊόν αυτό δεν µπορούν να αντικατασταθούν εύκολα από τους ίδιους τους χρήστες //les batterie(s présente(s) dans ce produit ne peuvent être facilement remplacée(s) par les utilisateurs eux-mêmes. orisnik ne može lako zamijeniti Bateriju sam u ovom proizvodu. batteria/le batterie in questo prodotto no può/possono essere facilmente sostituita/e dall'utente. etotăji paši nevar nomainīt šā ražojuma akumulatoru(-us). o gaminio baterijos [bateriju] pats vartotojas negali lengvai pakeisti.	batterija/bat	teriji f'dan il-prodott ma tistax	/jistgħux tiġi/jiġu sostitwita/i mill-utenti stess.					
s baterías de este produčto no pueden ser sustituidas fácilmente por los propios usuarios. iměnu baterie/baterií v tomto výrobku by neměli provádět sami uživatelé. ugeren kan likke uden videre udskifte batteriet/batterierne i dette produkt. ar Akku/die Akkus dieses Produkts kann/können nicht ohne weiteres vom Benutzer selbst ausgetauscht werden. Isutajad ei saa selle toote akut/akusid ise hôlpsasti asendada. µmardpálq=c5] dro mpoïóv aurō čev µmopoúv va dvnkardarde0úv sůkoλα από rouç ίδιους rouς χρήστες /les batterie(s présente(s) dans ce produit ne peuvent être facilement remplacée(s) par les utilisateurs eux-mêmes. prisnik ne može lako zamijeniti Bateriju sam u ovom proizvodu. I batteria/le batterie in questo prodotto non può/possono essere facilmente sostituita/e dall'utente. stotaji nevar nomainīt šā ražojuma akumulatoru(-us). o gaminio baterijos [bateriju] pats vartotojas negali lengvai pakeisti. termék akkumulátorát/akkumulátorai ta felhasználó nem tudja egysedül egyszerűen kicserélni. batteria/batteriji f'dan il-prodott ma tistax/jistgňux tiģi/jű vostitiwita/i mill-utenti stess.	e batterij(en) in dit product is (zijn) door d	e gebruiker niet gemakkelijk vervangbaar.					
s baterías de este producto no pueden ser sustituidas fácilmente por los propios usuarios. iměnu baterie/bateríl v tomto výrobku by neměli provádět sami uživatelé. ugeren kan ikke uden videre udskifte batteriet/batterierne i dette produkt. er Akku/die Akkus dieses Produkts kann/können nicht ohne weiteres vom Benutzer selbst ausgetauscht werden. asutajad ei saa selle toote akut/akusid ise hõlpsasti asendada. µrmarapíd[-sc] oro mpoïóv auró šev µrmopoúv va αντικατασταθούν εύκολα από τους ίδιους τους χρήστες //les batterie(s présente(s) dans ce produit ne peuvent être facilement remplacée(s) par les utilisateurs eux-mêmes. risnik ne može lako zamijeniti Bateriju sam u ovom proizvodu. I batteria/le batterie in questo prodotto non può/possono essere facilmente sostituita/e dall'utente. etotāji paši nevar nomainīt šā ražojuma akumulatoru(-us). o gaminio baterijos [bateriju] pats vartotojas negali lengvai pakeisti. termék akkumulátorát/vakkumulátorait a felhasználó mut dja egyedül egyszerűen kicserélni.	żytkownik ni	ie może sam w łatwy sposób	wymienić baterii w tym produkcie. ser facilmente substituídas pelos próprios utilizadores.					

A ou as baterias deste produto não podem ser facilmente substituídas pelos próprios utilizadore Bateria (bateriile) din acest produs nu poate (pot) fi uşor înlocuită (înlocuite) de utilizatorii înşişi. Batériu(-ie) v tomto výrobku nemôže vymieňať používateľ. Baterij/baterije v tem izdelku uporabniki sami ne morejo zlahka zamenjati. Tämän tuotteen akku [akut] ei[vät] ole helposti käyttäjän vaihdettavissa. Det är inte enkelt för kunden att själv byta ut batteriet/batterierna. Bu üründeki batarya(lar) kullanıcılar tarafından kolaylıkla değiştirilemez.